

ARIA GSM 4G VOLTE ROUTER FCT



VOLTE ENABLED – GSM FCT
Compatible with JIO SIM

Features

- ✓ Compatible with JIO SIMs. Connects to VOLTE/ 4G/3G/2G SIM.
- ✓ Provides a GSM interface to a PBX or Telephone Set.
- ✓ Can be connected to a PBX or directly to a Telephone Set.
- ✓ LED Indications to show GSM Signal Strength.
- ✓ STD Code Addition : In direct local dialing, no need to pre-fix area code
- ✓ Caller ID generation

Technical Specifications

Power Input	220V AC at 50Hz
Power Consumption	Standby = 2 Watts During Talk = 5 Watts
Networks Supported	GSM 850/900/1800/1900 MHZ; CDMA 800 MHZ; 3G WCDMA; 2G / 3G / 4G /LTE
SIM Socket	Standard Mini (2FF). Hinge Slie Lock mechanism.
Max. Loop Current of Telephone Line Port	30 mA
Max. Loop Resistance of Telephone Line Port	1,250 Ohms
Mounting Type	Can be placed on Table TOP or Wall Mounted.
Housing	Moulded from A Grade ABS
Dimensions	108 mm x 140 mm x 35 mm
Weight	270 Gms
Communication	Full Duplex Communication.
Ring Voltage generated on Telephone Line Port	63V AC at 20Hz
Signal Strength Display	Through 6 LEDs
GSM Antennae	Spiral Type GSM Antennae with SMA Connector (Gold Plated), 10 ft wire length, Magnetic Base and 3dBi Gain.
Ambient conditions for operation	Ventilated 0 to 45°C and max. 95% Non Condensing Humidity.

Call us Now:

Sales ID:- Sales@ariasolutions.net
Sales P:- 0120-4763988
Support ID:- support@ariasolutions.net
Support P:- 0120-4763963

Corporate Office: CS 40, 3rd Floor, Ansal Plaza, Sec - 1, Vaishali, Ghaziabad, UP - 201010 (India).
Registered Office: 106, Vardhman Master Plaza, Plot No - 2, Gazipur, New Delhi - 110096 (India).
website: www.ariatelecom.net www.arianamaste.com

Other Locations:

Lucknow Mumbai Bangalore Kolkata Hyderabad Chennai Chandigarh Indore